

FG8801N02 README Firmware Update v02.00


Remark

This guide describes the procedure to update the FG8801N02 from firmware version v01.06 to v02.00. If your FG8801N02 operates an older firmware version than v01.06, it is mandatory to update to version v01.06 before updating to version v02.00!

Update procedure

Follow the following steps to perform an update via huma®:

1. Click System on the upper left corner
2. Click Firmware Update in the left panel
3. Drag and drop the FG8801N02_update_v0200 file into the drag and drop field



4. After approximately 2 minutes the firmware update check page will be displayed. The FG8801N02 must be updated one after the other, so if more than one FG8801N02 is equipped in your system you have to deselect all but one, as shown in the following figure:

1 ————— 2 ————— 3
 Choose file Check Result

Overview

Selected file: **FG8801N02_update_v0200** Choose another file

Device	Position	Status	Version	Perform Update
FG8901P04	POS1	Unchanged	0102	<input type="checkbox"/>
FG8702G02	POS2	Unchanged	v0106	<input type="checkbox"/>
FG8801N02	POS3	Changed	v0106 >>> v0200	<input checked="" type="checkbox"/>
FG8801N02	POS4	Changed	v0106 >>> v0200	<input type="checkbox"/>
FG8101G01	system	Unchanged	v0104	<input type="checkbox"/>

Apply

Only one is selected and the other ones must be deselected

5. Click the Apply button to perform the update on the selected FG8801N02
6. The firmware update progress page is displayed

UPLOAD

 Firmware update in progress

ACTION

1 ————— 2 ————— 3
 Choose file Check Result

7. After approximately 4 minutes the firmware update is finished and the reboot screen is displayed
8. After 60 seconds the login page is displayed. After login you will realize that the FG8801N02 is not shown, that's because the management board has firmware version v01.06 and will not show FG8801N02 with v02.00 firmware.
9. Perform the steps 1 to 8 for the next FG8801N02 if another one exists, otherwise you are finished and can proceed with the firmware update of the management board in position 2